

**EQUINOX PARTS LIST****22nd January 2003**

Value	Location	Part Number	Description	Supplier
100k	R5,49,51,55,53,47,46,44,19,8	62-0964	MR25 0.25W 1%	Rapid
100R	R6	62-0762	"	"
10k	R1,17,23,50,54,27,52,35,31,56,10	62-0897	"	"
15k	R3	62-0907	"	"
1k	R22,30,26,34,59,43,39	62-0824	"	"
22k	R4	62-0922	"	"
22R	R41,42,57,58	62-0724	"	"
270k	R60	62-0987	"	"
27k	R21,32,28,25,24,33,29,15	62-0927	"	"
2k2	R7	62-0847	"	"
30k	R16,20	62-0932	"	"
330k	R45	62-0992	"	"
470k	R13,36	62-0997	"	"
47k	R37	62-0942	"	"
47R	R2	62-0737	"	"
4k7	R18,14,12	62-0862	"	"
56k	R11,40	62-0947	"	"
6k8	R9	62-0874	"	"
7k5	R38	62-0877	"	"
82k	R48	62-0957	"	"
100n	C4,11,2,20,21	10-3220	DMP5 Polyester	Rapid
22u	C5,1,13,12,14,15,8,7	11-0230	25V Radial Electrolytic	"
470n	C10,9,3,6	10-3228	DMP5 Polyester	"
6n8	C16,17,18,19	10-1455	100V Polypropylene	"
BC549B	Q1,3,4,5,6,7,8,9,10,11	81-0068	NPN Gen Purpose Transistor	Rapid
BC557B	Q2,12	81-0070	PNP Gen Purpose Transistor	"
TL072	U6,1	82-0050	Dual Low Noise Opamp	Rapid
CA3080A	U2,3,4,5	82-0682	Transconductance Opamp	"
470k	TUNE	67-0255	PNZ10Z Horizontal Preset	Rapid
10kB	EMPHASIS		OMEG	Oakley
47kA	FREQ, DEPTH		"	"
47kB	RATE		"	"
Pot Brackets	4 off		"	"
Ferrite	L1,2	26-4860	Leaded Ferrite Bead	Rapid
LED	LFO RATE	55-0172	5mm Red/Green LED	"
LENS		55-1030	Clear LED LENS	"
4 Way Header	1 off	22-2600	0.156" Straight Pin Header	Rapid
8 pin	6 off	22-0400	Low Pro Turned Pin IC Socket	"
Jack Socket	4 off	20-1430	Switchcraft 112APC	"
Knobs	4 off	32-0510	Sifam Soft touch collet 21mm	"
Caps	4 off	225-984	21mm C211 Lined Black	RS
Wire	Interconnect	01-0105	20m Stranded Pack	Rapid
Front Panel		equ.fpd		Schaeffer