

Superladder Iss 3 (Moog Option)

8th December 2003

| Value | Location | Part Number | Description | Supplier |
|--------------|-------------------------------------|-------------|------------------------------|-----------|
| 100k | R1,15,23,22,60,17,14,42,18,19,25,82 | 62-0964 | MR25 0.25W 1% | Rapid |
| 10k | R75,38,21,43,46,50,58,77,69 | 62-0897 | " | " |
| 15k | R47,20,67,48 | 62-0907 | " | " |
| 150R | R16 | 62-0767 | " | " |
| 1k | R79,44,5,4,32,57,6,9,10,12,11 | 62-0824 | " | " |
| 1k | R64 | | +3000ppm/K | Oakley |
| 200k | R62,53,59 | 62-0982 | MR25 0.25W 1% | Rapid |
| 22k | R40,29 | 62-0922 | " | " |
| 27k | R61 | 62-0927 | " | " |
| 330R | R35,34,66,26,30,63 | 62-0792 | " | " |
| 33k | R28,13,37 | 62-0934 | " | " |
| 390k | R49,74,80,78 | 62-0994 | " | " |
| 3k3 | R8,36,7 | 62-0892 | " | " |
| 47k | R2,3 | 62-0942 | " | " |
| 4k7 | R55,52,73,71 | 62-0862 | " | " |
| 560k | R41,27,65,45 | 62-1002 | " | " |
| 62k | R33 | 62-0949 | " | " |
| 680R | R68 | 62-0812 | " | " |
| 750k | R81,56 | 62-1005 | " | " |
| 33n | C7,8,9,10 | 10-3216 | Polyester DMP5 | Rapid |
| 100n | C20,13,15,16,6 | 10-3220 | " | " |
| 1n | C5,11,21 | 10-3200 | " | " |
| 1u | C19,22,14,3 | 10-3232 | " | " |
| 22u | C12,18,17 | 11-0230 | 25V Radial Electrolytic | " |
| 220u | C2 | 11-0260 | 16V Radial Electrolytic | " |
| BC549B | Q8,7,6,1,2,3 | 81-0068 | NPN GP Transistor | Rapid |
| BC558B | Q4,5 | 81-0072 | PNP GP Transistor | " |
| 1N4148 | D4,2,3 | 47-3308 | Signal Diode | " |
| TL072 | U8,10,3,2 | 82-0050 | Dual Low Noise Opamp | " |
| TL074 | U7,5 | 82-0054 | Quad Low Noise Opamp | " |
| LM13700N | U4 | 82-5038 | Dual Transconductance Opamp | " |
| CA3080E | U11 | 82-0682 | OTA | " |
| 20k | V/OCT | 68-0335 | " | Rapid |
| 100k | TUNE | 68-0345 | 3296W Multiturn Trimmer | " |
| 100k | BAL,OFF2,OFF1,CNTR,OFF3 | 67-0245 | Horizontal Trimmer | " |
| 1k | BPA | 67-0215 | " | " |
| 22k | TWEAK | 67-0235 | " | " |
| 10kA | RESONANCE | | Omeg Pot Linear | Oakley |
| 47kA | FREQ,SHAPE | | " | " |
| 22kA | ENV DEPTH | | " | " |
| 47kB | IN1,IN2,IN3 | | Omeg Pot Log | " |
| 100kA | EXP CV,LIN CV,RES CV,ENV MOD | | Omeg Pot Linear | " |
| Pot Brackets | 4 off | | " | " |
| Ferrite | F1,2 | 26-4860 | Leaded Ferrite Bead | Rapid |
| 4 Way Header | 1 off | 22-2600 | 0.156" Straight Pin Header | " |
| 8 pin | 5 off | 22-0400 | Low Pro Turned Pin IC Socket | " |
| 14 pin | 4 off | 22-0405 | " | " |
| 16 Pin | 1 off | 22-0410 | " | " |
| Jack Socket | 12 off | 20-1430 | Switchcraft 112APC | " |
| Knobs | 11 off | 32-0510 | Sifam Soft touch collet 21mm | " |
| Caps | 11 off | 225-984 | 21mm C211 Lined Black | RS |
| Wire | Interconnect | 01-0105 | 20m Stranded Pack | Rapid |
| Front Panel | | super.fpd | | Schaeffer |